



IEC 61800-9-2

Edition 2.1 2025-12

INTERNATIONAL STANDARD

CONSOLIDATED VERSION

**Adjustable speed electrical power drive systems (PDS) -
Part 9-2: Ecodesign for motor systems - Energy efficiency determination and
classification**

CONTENTS

FOREWORD	8
INTRODUCTION	10
1 Scope	11
2 Normative references	12
3 Terms, definitions and symbols	13
3.1 Terms and definitions	13
3.2 Symbols	17
4 PDS efficiency, reference CDM (RCDM) and reference motor (RM)	26
4.1 General	26
4.2 Reference operating points of the PDS, RCDM, RM and associated losses	26
4.3 Combining PDS losses with the driven equipment – Workflow for the semi-analytical model (SAM)	28
4.4 IE Classes of line-fed motors	30
4.5 IE Classes of converter-fed motors	30
4.6 IE Classes of frequency converters (complete drive modules, CDM)	30
4.7 IES Classes of a PDS	31
4.8 Consistency of IE and IES Classes	31
4.9 Determination of the IES class of a PDS by application of "reference" and "test" devices and guidance for the providers	32
5 Determination of CDM, motor and PDS loss by calculation	33
5.1 General	33
5.2 CDM losses	34
5.2.1 General procedure and definition of the CDM and the test load	34
5.2.2 Overall CDM losses	36
5.2.3 Loss determination of CDMs composed by combination of submodules	37
5.2.4 Validation of loss calculation method	39
5.3 Motor losses	39
5.3.1 General	39
5.3.2 Additional harmonic losses of three-phase asynchronous motors fed by a CDM	40
5.3.3 Motor loss data	40
5.4 Power drive system (PDS) losses	40
5.4.1 PDS losses	40
5.4.2 PDS losses at different switching frequencies	42
5.5 PDS losses for regenerative operation	43
5.6 Losses of motor starters	43
6 Limits of IE and IES Classes	43
6.1 General	43
6.2 CDM	44
6.3 Correction factors for CDMs with modified functionality	46
6.3.1 General	46
6.3.2 Correction factors	48
6.3.3 Reference losses and loss determination concept for CDMs and SDOMs with multiple AC outputs	49
6.4 Motor	50
6.5 PDS	50
7 Loss determination	51

7.1	General.....	51
7.2	Type testing of CDM or SDM for IE classification	52
7.3	Type testing of PDS for IES classification	53
7.4	Determination of losses by calculation	53
7.4.1	CDM or SDM losses by calculation	53
7.4.2	PDS losses by calculation.....	54
7.5	Determination of losses by measurement, Input-output method.....	54
7.5.1	Instrumentation.....	54
7.5.2	Test conditions	55
7.5.3	Input-output measurement of CDM losses	56
7.5.4	Input-output measurement of SDIM losses.....	58
7.5.5	Input-output measurement of SDOM losses	60
7.5.6	Input-output measurement of PDS losses	61
7.6	Calorimetric measurement of CDM losses.....	62
7.7	Flowcharts for test procedures	63
8	Requirements for the user's documentation	67
8.1	General.....	67
8.2	Information for selection	68
8.3	Information for determination of energy efficiency classification	68
8.4	Information on the determination of additional energy losses and part load conditions	68
8.4.1	General	68
8.4.2	Losses in part load conditions.....	68
8.4.3	Losses of accessories and options	69
8.4.4	Losses in stand-by mode	69
8.4.5	Regenerative mode	69
8.4.6	Characteristics and correction factors.....	69
Annex A (informative)	Losses of RCDM and example of IES class limit determination	70
A.1	Relative loss tables.....	70
A.2	Calculation of relative losses for IES classes	71
A.2.1	General	71
A.2.2	Determination of CDM relative losses	71
A.2.3	Determination of motor relative losses	72
A.2.4	Summation of PDS relative losses	72
Annex B (informative)	Description of the elements of an extended product using PDS with regard to their impact on losses.....	73
B.1	General.....	73
B.2	Losses in the mains cabling and feeding section.....	73
B.3	Input filter	75
B.3.1	High frequency EMI filter	75
B.3.2	Low frequency line harmonics filter.....	75
B.4	Input converter.....	76
B.4.1	General	76
B.4.2	Diode rectifier.....	76
B.4.3	Active infeed converter	77
B.4.4	Power factor of the input converter	78
B.4.5	Sub drive input module (SDIM)	79
B.5	DC link.....	79

B.6	Output inverter	81
B.6.1	General	81
B.6.2	Sub drive output model (SDOM)	81
B.7	Output filter and motor cables	81
B.7.1	General	81
B.7.2	Sine wave filters	82
B.7.3	dV/dt filters and motor chokes	83
B.7.4	High frequency EMI motor filters	84
B.7.5	Motor cables	84
B.8	Motor	84
B.9	Mechanical load	84
B.10	Control and standby losses	84
B.11	Cooling losses	84
B.11.1	Primary cooling losses	84
B.11.2	Secondary cooling losses	85
Annex C (informative)	Mathematical model for CDM losses	86
C.1	General	86
C.2	Output inverter losses	86
C.2.1	General	86
C.2.2	Transistor on state losses	86
C.2.3	Freewheeling diode on state losses	87
C.2.4	Transistor switching losses	87
C.2.5	Freewheeling diode switching losses	88
C.2.6	Output inverter total losses	89
C.3	Input converter losses	89
C.3.1	Active infeed converter	89
C.3.2	Diode rectifier	89
C.4	Input choke losses	90
C.5	DC link losses	91
C.6	Current conductor losses	91
C.7	Control and standby losses	92
C.8	Cooling loss factor	92
C.9	Other CDM losses	92
Annex D (informative)	Converter topology	93
D.1	General	93
D.2	Voltage source output inverter topologies different from those mathematically described in Clause C.2	93
D.3	Voltage source input converter topologies different from those mathematically described in Clause C.3	93
D.4	CDM topologies different from voltage source type	94
Annex E (informative)	Interpolation of motor losses and motor current	95
E.1	General	95
E.2	Relative and reference values	95
E.3	Motor connections and operating ranges	96
E.4	Interpolation of motor losses	97
E.5	Interpolation of motor current	100
E.6	Determination of the interpolation coefficients	102
E.6.1	General	102

E.6.2	Analytical determination	102
E.6.3	Numerical determination	104
E.7	Achievable accuracies	105
E.8	Typical induction motor efficiency	105
Annex F (informative)	Application example for loss calculations of a CDM and a PDS	111
F.1	General.....	111
F.2	CDM loss determination.....	111
F.2.1	General	111
F.2.2	Loss determination by two-dimensional interpolation of losses of neighbouring loss points	112
F.2.3	Loss determination by the mathematical model described in Annex C.....	115
F.3	Loss determination of the motor	117
F.4	Loss determination of the PDS.....	118
F.5	Determination of part load factors for SDIMs.....	119
F.6	Application examples of reference losses and efficiency classes for modified functionality	120
F.6.1	General	120
F.6.2	Example 1 – IE classification of an SDIM.....	120
F.6.3	Example 2 – IE classification of an SDOM	120
F.6.4	Example 3 – IE classification of a CDM with regenerative capability and sinewave output filter.....	121
Annex G (informative)	Uncertainty of loss determination method	123
G.1	General.....	123
G.2	Calculation of uncertainty at randomly occurring errors	123
G.3	Comparison of uncertainties for different loss determination methods	123
Annex H (informative)	Calorimetric measurement for CDM losses.....	124
H.1	General.....	124
H.2	Calorimeter with two chambers with air as a cooling medium	124
H.3	Calorimeter with one chamber with air as a cooling medium	125
H.4	Calorimeter with liquid as a cooling medium.....	126
Annex I (informative)	PDS loss calculation above rated speed and torque	127
I.1	General.....	127
I.2	Operating points above rated torque	127
I.3	Operating points above rated speed.....	127
I.3.1	General	127
I.3.2	Dependency of motor losses on the CDM performance.....	127
I.3.3	Dependency of CDM on the motor performance.....	128
I.3.4	PDS loss calculation in the field weakening range up to 200 % of rated speed	128
Annex J (informative)	Explanation for correction factors for the reference losses in Table 8	129
J.1	General.....	129
J.2	CDM	129
J.2.1	CDM without regenerative capability.....	129
J.2.2	CDM with regenerative capability.....	130
J.2.3	CDM with $DF_U \leq 10\%$	131
J.2.4	CDM with a rated input voltage $\leq 250\text{ V}$ (three phase)	131
J.2.5	CDM with single phase input.....	131
J.3	SDIM and SDOM	132

J.3.1	General	132
J.3.2	SDIM without regenerative capability	132
J.3.3	SDIM with regenerative capability	132
J.3.4	SDOM	133
J.4	CDM, SDIM and SDOM with external cooling	133
J.5	CDM and SDOM with multiple AC outputs	133
	Bibliography	134

Figure 1 – Example of complete drive module (CDM) built by sub drive modules (SDM)	14
Figure 2 – Illustration of the extended product with included motor system	15
Figure 3 – Torque-speed-characteristic of servo PDS	16
Figure 4 – Illustration of the operating points (shaft speed, torque) for the determination of relative losses of the power drive system (PDS)	27
Figure 5 – Illustration of the operating points (shaft speed, torque) for the determination of relative losses of the reference motor (RM)	27
Figure 6 – Illustration of the operating points (relative motor stator frequency, relative torque current) for the determination of losses of the reference complete drive module (RCDM)	28
Figure 7 – Illustration of the workflow to determine the energy efficiency index (EEI) of an extended product	29
Figure 8 – Illustration how to combine different data sources to determine the energy efficiency index (EEI) of an extended product	30
Figure 9 – Metrical relation	32
Figure 10 – Guidance for CDM and motor providers for the usage of "test" and "reference" devices to determine the IE/IES classes	33
Figure 11 – Illustration of a typical CDM and test load	34
Figure 12 – Example of relative losses $p_{L,CDM}$ of the 9,95 kVA RCDM	37
Figure 13 – Example of the relative power losses of PDS as function of speed and torque	42
Figure 14 – Example representation of the relative power losses versus switching frequency of a 7,5 kW to 11 kW PDS	42
Figure 15 – Example of a CDM with resistor for dissipating generated power	43
Figure 16 – Illustration of IE Classes for a CDM	46
Figure 17 – Topology of a CDM with multiple AC outputs	49
Figure 18 – Losses of CDM or SDM are provided as the sum of the determined losses plus the uncertainty of the determination method	52
Figure 19 – Input-output measurement setup for determination of CDM losses	57
Figure 20 – Order of CDM measurements from [1] to [8]	57
Figure 21 – Input-output measurement setup for determination of SDIM losses	59
Figure 22 – Input-output measurement setup for determination of SDOM losses	60
Figure 23 – Input-output measurement setup for PDS losses	61
Figure 24 – Order of PDS measurements from [1] to [8]	62
Figure 25 – Calorimetric measurement setup for determining CDM losses	63
Figure 26 – Determination of IE classification for CDM and loss determination for part load operating points	65
Figure 27 – Determination of IES classification for PDS and loss determination for part load operating points	66

Figure B.1 – Overview of the extended product and energy flow	73
Figure B.2 – Equivalent circuit of the mains and mains cabling	74
Figure B.3 – Illustration of a single-phase line harmonics filter	75
Figure B.4 – PDS with a diode rectifier input converter	76
Figure B.5 – PDS with a standard AIC input converter	77
Figure B.6 – PDS with a F3E-AIC input converter without line choke.....	78
Figure B.7 – Typical waveform of a diode rectifier line current	78
Figure B.8 – DC link circuit	79
Figure B.9 – DC link circuit with additional DC chokes	80
Figure B.10 – Output inverter of the PDS	81
Figure B.11 – Motor cable and optional output filter of the PDS	82
Figure B.12 – Typical waveform of inverter output voltage and motor voltage when using a sine wave output filter.....	83
Figure E.1 – Normalized torque and speed of ranges a and b for connection Y or D	96
Figure E.2 – Normalized torque and speed of ranges a and b for connection Y → D	97
Figure E.3 – Normalized torque and speed of range a for connection Y → YY	97
Figure E.4 – Normalized losses of an exemplary motor in connection Y or D	98
Figure E.5 – Normalized losses of an exemplary motor in connection Y → D	98
Figure E.6 – Normalized losses of an exemplary motor in connection Y → YY	99
Figure E.7 – Efficiency map of the exemplary motor in connection Y or D	99
Figure E.8 – Efficiency map of the exemplary motor in connection Y → D	100
Figure E.9 – Efficiency map of the exemplary motor in connection Y → YY.....	100
Figure E.10 – Line-current of the exemplary motor in connection Y or D	101
Figure E.11 – Line-current of the exemplary motor in connection Y → D	101
Figure E.12 – Line-current of the exemplary motor in connection Y → YY	102
Figure E.13 – Standardized operating points of IEC 60034-2-3	103
Figure F.1 – Segments of operating points.....	111
Figure F.2 – Two-dimensional interpolation.....	112
Figure H.1 – One-step calorimetric measurement setup for comparative loss measurement (CDM and heating resistor are loaded simultaneously)	124
Figure H.2 – Two-step calorimetric measurement setup for comparative loss measurement (CDM and heating resistor are not loaded simultaneously).....	125
Figure H.3 – Liquid cooled calorimetric measurement setup for CDM loss measurement	126
Table 1 – Minimum test load currents at different points of operation	35
Table 2 – Test load displacement factor between fundamental output current and fundamental output voltage at different points of operation	35
Table 3 – Example of relative losses of the 400 V/9,95 kVA reference CDM at the operating points described in Figure 6	37
Table 4 – Active SDIM power ratio to be used for loss calculation at the CDM operating points	39
Table 5 – Reference parameter for Formula (13)	41
Table 6 – Relative losses of the 400 V/7,5 kW PDS	41
Table 7 – Reference CDM losses for class IE1 definition	44

Table 8 – Correction factors for different CDM, SDIM and SDOM characteristics	48
Table 9 – Information requirements.....	67
Table A.1 – Relative losses (%) of reference CDMs (IE1) at different power ratings at the operating points described in Figure 6	70
Table A.2 – Relative losses of the 9,95 kVA CDM according to Table A.1	71
Table B.1 – Typical values of λ for different input converter topologies	79
Table C.1 – Reference parameters for Formula (C.1).....	86
Table C.2 – Variables for Formula (C.1).....	87
Table C.3 – Reference parameters for Formula (C.2).....	87
Table C.4 – Reference parameters for Formula (C.3).....	88
Table C.5 – Reference parameters for Formula (C.4).....	88
Table C.6 – Reference parameters for Formula (C.6).....	90
Table C.7 – Variables for Formula (C.6).....	90
Table C.8 – Reference parameters for Formula (C.7).....	90
Table C.9 – Reference parameters for Formula (C.8).....	91
Table C.10 – Reference parameters for Formula (C.9).....	91
Table C.11 – Reference parameter for Formula (5)	92
Table C.12 – Reference parameter for Formula (C.10).....	92
Table E.1 – Normative operating points of IEC 60034-2-3.....	102
Table E.2 – Interpolation coefficients of typical 4-pole IE2 induction machines	106
Table E.3 – Interpolation coefficients of typical 2-pole IE2 induction machines	107
Table E.4 – Interpolation coefficients of typical 4-pole IE3 induction machines	108
Table E.5 – Interpolation coefficients of typical 4-pole IE4 induction machines	109
Table E.6 – Interpolation coefficients of typical 4-pole IE5 induction machines	110
Table F.1 – Relative losses of a 400 V/9,95 kVA example CDM (IE1) at the predefined operating points	112
Table F.2 – Parameters of the example CDM.....	116
Table F.3 – Results of the CDM calculation according to the mathematical model.....	117
Table F.4 – Comparison of different loss evaluation methods.....	117
Table F.5 – Loss data of the 7,5 kW example motor.....	117
Table F.6 – Calculated part-load factors for SDIM part load operation points	119

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**Adjustable speed electrical power drive systems (PDS) -
Part 9-2: Ecodesign for motor systems -
Energy efficiency determination and classification**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendment has been prepared for user convenience.

IEC 61800-9-2 edition 2.1 contains the second edition (2023-10) [documents 22G/475/FDIS and 22G/478/RVD] and its amendment 1 (2025-12) [documents 22G/522A/CDV and 22G/527/RVC].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendment 1. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.

IEC 61800-9-2 has been prepared by subcommittee 22G: Adjustable speed electric drive systems (PDS), of IEC technical committee 22: Power electronic systems and equipment. It is an International Standard.

This second edition cancels and replaces the first edition published in 2017. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) Additional IES Classes defined to IES5;
- b) Removed reference motor loss data and now point to IEC 60034-30-2;
- c) Expanded and modified factors in Clause 6 for CDMs;
- d) Annex C is now the Mathematical Model for CDM Losses;
- e) Moved the mathematical model for the CDM to Annex C;
- f) Added Sub Drive Input Module and Sub Drive Output Modules to Annex B;
- g) Annex D is now the Converter Topology (old Annex C);
- h) Annex E is now the Interpolation of Motor Losses (Old Annex D);
- i) Annex E expanded to include various motor connections and updated interpolation method;
- j) New Annex E for determination of Interpolation Coefficients;
- k) Annex F is the old Annex E;
- l) New Annex J Explanation of Correction Factors for the Reference Losses in Table 8.

The text of this International Standard is based on the following documents:

Draft	Report on voting
22G/475/FDIS	22G/478/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts in the IEC 61800 series, published under the general title *Adjustable speed electrical power drive systems (PDS)*, can be found on the IEC website.

The committee has decided that the contents of this document and its amendment will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

This corrected version of IEC 61800-9-2:2023 incorporates the following correction:

- Removal of the status of group energy efficiency publication, previously mentioned on the cover pages, in the foreword, and in the scope.

INTRODUCTION

This part of IEC 61800 has been developed to allow evaluation of power losses of SDMs (sub drive modules), CDMs (complete drive modules) and PDSs (power drive systems).

The requirements for measuring energy efficiency of motors with non-sinusoidal supply are under the responsibility of IEC/TC 2 and will be published under the IEC 60034 series.

IEC SC 22G includes the standardization task force for dealing with this topic. It has close collaboration with several other technical committees (for example, IEC TC 2, IEC SC 121A, ISO/TC 115, ISO/TC 117, ISO/TC 118, CEN/TC 197) in order to provide a comprehensive standard for energy efficiency and ecodesign requirements.

IEC SC 22G maintains responsibility for all relevant aspects in the field of energy efficiency and ecodesign requirements for power electronics, switchgear, control gear and power drive systems and their industrial applications.

The IEC 61800 series does not deal with mechanical engineering components.

NOTE 1 Geared motors (motors with directly adapted gearboxes) are treated like power drive systems (converter plus motor). See IEC 60034-30-1 for classification of the losses of a geared motor. The efficiency classes of gearboxes as individual components are under consideration.

IEC 61800-9-2 is a subpart of the IEC 61800 series, which has the following structure:

- Part 1: General requirements – Rating specifications for low voltage adjustable speed DC power drive systems
- Part 2: General requirements – Rating specifications for adjustable speed AC power drive systems
- Part 3: EMC requirements and specific test methods
- Part 5: Safety requirements
- Part 6: Guide for determination of types of load duty and corresponding current ratings
- Part 7: Generic interface and use of profiles for power drive systems
- Part 8: Specification of voltage on the power interface
- Part 9: Ecodesign for motor systems

Some parts are further subdivided into several subparts, published either as International Standards or as Technical Specifications or Technical Reports and will be published with the part number followed by a dash and a second number identifying the subdivision (example: IEC 61800-9-2).

NOTE 2 It is understood that Formula (13) is for Direct-on-Line motors. Formula (13) will be modified in the next amendment to account for Variable Frequency Drive motors.

NOTE 3 A new figure will be developed to demonstrate the use of a star point for measuring the converter phase voltages to determine the $\cos\phi$ for each phase in 7.5.3.1.

1 Scope

This part of IEC 61800 specifies energy efficiency indicators of power electronics (complete drive modules (CDM), input or output sub drive modules (SDM), power drive systems (PDS) and motor starters, all used for motor driven equipment.

This document specifies the methodology for the determination of losses of the complete drive module (CDM), the sub drive module (SDM), the power drive system (PDS) and the motor system.

It defines IE and IES classes, their limit values and provides test procedures for the classification of the overall losses of the motor system.

Furthermore, this document proposes a methodology for the implementation of the best energy efficiency solution of drive systems. This depends on the architecture of the motor driven system, on the speed/torque profile and on the operating points over time of the driven load equipment. It provides a link for the energy efficiency evaluation and classification of the extended product.

The methodology of the extended product approach and the semi analytical models are defined in IEC 61800-9-1.

The structure of this document is as follows:

- the losses of standardized PDS, standardized reference CDM (RCDM) and the mathematical model for their calculation are given and classified;
- the reference motor (RM) and the reference CDM (RCDM) are defined. They are used for determining the efficiency class of a PDS if either the physical motor or physical CDM is unknown;
- the requirements for the determination of the losses of a physical PDS and a physical CDM including correction factors for other types of CDM, not defined as RCDM or SDM, are given and compared to the IES class limits and the RCDM;
- the requirements for type testing and user documentation are given;
- some exemplary losses of an overall system are illustrated in annexes;
- information about system and drive topologies are given in annexes.

Specific data for the RCDM and RM, limits for the PDS and IE/IES classes are given for low voltage (100 V up to and equal to 1 000 V), single axis AC/AC power drive systems with three-phase motors. Geared motors are treated as standard motors when motor and gearbox can be separated. A methodology is given in addition how this reference data can also be applied to other topologies like AC/DC or DC/AC converters.

All provided reference data is derived from PDS with induction motors. They can be used for various types of PDS with other types of motors as well, for example but not limited to, electronically commutated motors (ECM), permanent magnet motors (PM) or synchronous reluctance motors (SYN-RM), and line-start permanent magnet motors (LSPM).

PDS requirements in this document only apply to PDSs that are placed on the market as one single product, i.e. combination of motor and CDM that are not intended to be used separately.

CDM requirements only apply to a CDM where the included SDMs have not already been evaluated according to SDM requirements.

The following equipment is excluded from the scope:

- high voltage CDM, SDM and PDS with a rated voltage above 1,0 kV AC or 1,5 kV DC;

- low voltage CDM, SDM and PDS with a rated voltage below 100 V AC;
- high power PDS above a rated power of 1 000 kW;
- high power CDM and SDM above a rated apparent output power of 1 209 kVA;
- low power PDS below a rated power of 0,12 kW;
- low power CDM and SDM below a rated apparent output power of 0,278 kVA;
- PDS with geared motors where motor and gearbox cannot be separated, for example because of a common housing;
- servo PDS (consisting of frequency converter, motor and position feedback sensor);
- CDM, BDM and SDM that are exclusively designed to drive servo motors;
- PDS, CDM, BDM and SDM specifically designed for DC motor applications according to IEC 61800-1;
- PDS where several motors are connected in parallel to a single CDM with one three-phase output.
- SDM with DC input and DC output.

NOTE The IEC 61800-9 series does not cover energy efficiency classification of driven equipment but provides input for the assessment according to the extended product approach.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034-1:2022, *Rotating electrical machines – Part 1: Rating and performance*

IEC 60034-2-1:2014, *Rotating electrical machines – Part 2-1: Standard methods for determining losses and efficiency from tests (excluding machines for traction vehicles)*

IEC 60034-2-3:2020, *Rotating electrical machines – Part 2-3: Specific test methods for determining losses and efficiency of converter-fed AC induction motors*

IEC 60034-30-1:2014, *Rotating electrical machines – Part 30-1: Efficiency classes of line operated AC motors (IE code)*

IEC TS 60034-30-2:2016, *Rotating electrical machines – Part 30-2: Efficiency classes of variable speed AC motors (IE-code)*

IEC TS 60034-31:2021, *Rotating electrical machines – Part 31: Selection of energy-efficient motors including variable speed applications – Application guidelines*

IEC 60038:2009, *IEC standard voltages*
IEC 60038:2009/AMD1:2021

IEC 60050-161, *International Electrotechnical Vocabulary (IEV) – Part 161: Electromagnetic compatibility*, available at www.electropedia.org

IEC 60947-4-1:2018, *Low voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 61000-3-12:2011, *Electromagnetic compatibility (EMC) – Part 3-12: Limits – Limits for harmonic currents produced by equipment connected to public low-voltage systems with input current $> 16\text{ A}$ and $\leq 75\text{ A}$ per phase*

IEC Guide 118:2017, *Inclusion of energy efficiency aspects in electrotechnical publications*

Bibliography

IEC 60034 (all parts), *Rotating electrical machines*

IEC TS 60034-25, *Rotating electrical machines – Part 25: AC electrical machines used in power drive systems – Application guide*

IEC 60034-30, *Rotating electrical machines – Efficiency classes*

IEC 60146-1-1, *Semiconductor converters – General requirements and line commutated converters – Part 1-1: Specification of basic requirements*

IEC 60947-4-2, *Low-voltage switchgear and controlgear – Part 4-2: Contactors and motor-starters – Semiconductor motor controllers, starters and soft-starters*

IEC 61800-1, *Adjustable speed electrical power drive systems – Part 1: General requirements – Rating specifications for low voltage adjustable speed DC power drive systems*

IEC 61800-2, *Adjustable speed electrical power drive systems – Part 2: General requirements – Rating specifications for adjustable speed AC power drive systems*

IEC 61800-3, *Adjustable speed electrical power drive systems – Part 3: EMC requirements and specific test methods for PDS and machine tools*

IEC 61800-5-1, *Adjustable speed electrical power drive systems – Part 5-1: Safety requirements – Electrical, thermal and energy*

IEC TS 61800-8:2010, *Adjustable speed electrical power drive systems – Part 8: Specification of voltage on the power interface*

IEC 61800-9-1, *Adjustable speed electrical power drive systems – Part 9-1: Ecodesign for power drive systems, motor starters, power electronics and their driven applications – General requirements for setting energy efficiency standards for power driven equipment using the extended product approach (EPA) and semi analytic model (SAM)*

IEC TS 62578:2015, *Power electronics systems and equipment – Operation conditions and characteristics of active infeed converter (AIC) applications including design recommendations for their emission values below 150 kHz*

IEEE 112, *Standard Test Procedure for Polyphase Induction Motors and Generators*

CSA 838-13, *Energy efficiency test methods for three-phase variable frequency drive systems*