

# TECHNICAL REPORT

# IEC TR 62383

First edition  
2006-01

---

---

## **Determination of magnetic loss under magnetic polarization waveforms including higher harmonic components – Measurement, modelling and calculation methods**

© IEC 2006 — Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembé, PO Box 131, CH-1211 Geneva 20, Switzerland  
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: [inmail@iec.ch](mailto:inmail@iec.ch) Web: [www.iec.ch](http://www.iec.ch)



Commission Electrotechnique Internationale  
International Electrotechnical Commission  
Международная Электротехническая Комиссия

PRICE CODE

V

*For price, see current catalogue*

## CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
1 Scope.....	7
2 Normative references .....	7
3 Principles of measurement .....	7
3.1 General.....	7
3.2 Yokes, windings and test specimen .....	8
3.3 Power amplifier .....	8
3.4 Waveform synthesizer .....	8
3.5 Digitiser.....	8
3.6 Control of secondary voltage .....	9
3.7 Peak reading apparatus .....	9
3.8 Air flux compensation .....	9
4 Measuring system .....	10
5 Measurements.....	10
5.1 Generation of the magnetic polarization waveform including higher harmonics .....	10
5.2 Determination of peak value of magnetic polarization .....	11
5.3 Determination of the magnetic polarization .....	11
5.4 Determination of magnetic field strength.....	12
5.5 Determination of the magnetic loss.....	12
5.6 Plotting the a.c. hysteresis loop including the higher harmonics .....	12
6 Example of measurement .....	12
6.1 Magnetic loss measurement of non-oriented electrical steel sheets .....	12
6.2 Magnetic loss measurement under stator tooth waveform conditions .....	13
7 Prediction of magnetic loss including higher harmonic polarization .....	17
7.1 General .....	17
7.2 Energy loss separation [14] .....	17
7.3 Neural network method [17].....	23
7.4 Modified superposition formula [20].....	25
8 Summary.....	30
Bibliography.....	31
Figure 1 – Block diagram of the measuring system for the measurement of magnetic loss of electrical steel sheets under magnetic polarization waveforms which include higher harmonic components .....	10
Figure 2a – Magnetic polarization $J(t)$ .....	13
Figure 2b – Magnetic field strength $H(t)$ .....	14
Figure 2c – AC hysteresis loops.....	14
Figure 2 – Dependency on the higher harmonic polarization components of the magnetic polarization $J(t)$ ; magnetic field strength $H(t)$ , and a.c. hysteresis loops of non-oriented electrical steel at a fundamental magnetizing frequency $f_1 = 60$ Hz and a maximum magnetic polarization $\hat{J} = 1,5$ T, and for higher harmonic frequency of $f_h = 23f_1$ .....	14

Figure 3 – Specific total loss depending on the higher harmonic frequency and higher harmonic polarization for the non-oriented electrical steel sheet at $\hat{J} = 1,5 \text{ T}$ .....	15
Figure 4 – B-coil winding positions of stator tooth of a 3,75 kW induction motor to measure the a.c. hysteresis of the stator tooth depending on the load .....	16
Figure 5 – AC hysteresis loop of the stator teeth of a 3,75 kW induction motor measured in single sheet tester .....	16
Figure 6 – Specific total loss of the stator tooth depending on the load .....	17
Figure 7 – Examples of experimental dependence of the quantity $W_{dif} = W - W_{cl} = W_h + W_{exc}$ on the square root of frequency in grain-oriented Fe-Si laminations (thickness 0,29 mm).....	19
Figure 8 – Energy loss per cycle $W$ and its analysis in a non-oriented Fe-(3wt %)Si lamination energy loss with arbitrary flux waveform and minor loops.....	20
Figure 9 – Examples of composite experimental (solid lines) and reconstructed (dashed lines) d.c. hysteresis loops at peak magnetization $\hat{J} = 1,4 \text{ T}$ in non-oriented Fe-(3 wt %) Si laminations (thickness 0,34 mm) generated by the $J(t)$ waveforms .....	22
Figure 10 – Experimental dependence of the statistical parameter of the magnetization process $V_o$ on the peak magnetization value in the tested non-oriented Fe-Si laminations .....	22
Figure 11 – Loss evolution with the number of minor loops in a non-oriented Fe-Si lamination, subjected to controlled constant magnetization rate $\left  \frac{dJ(t)}{dt} \right  = 4f \cdot (\hat{J} + 2J_m)$ , with $\hat{J} = 1,4 \text{ T}$ and $2nJ_m = 1,2 \text{ T}$ .....	23
Figure 12 – Artificial neuron (also termed as unit or nodes) .....	23
Figure 13 – Neural network design topology .....	24
Figure 14 – Waveforms of $\frac{dJ(t)}{dt}$ , $H(t)$ and $J(t)$ when higher harmonic polarization is included .....	26
Figure 15 – Generation of two symmetrical a.c. minor loop measured in zero polarization region, and in saturation polarization region, of the fundamental hysteresis loop; magnetization in the rolling direction and perpendicular to the rolling direction.....	27
Figure 16 – Specific total loss $P_c$ of the combined waves, with harmonic frequency $23f_1$ , depending on the position of a.c. minor loop at maximum magnetic polarization of 1,0 T and of 1,5 T respectively.....	27
Figure 17 – Specific total loss depending on the higher harmonic frequency .....	29
Figure 18 – Constant $k_2$ vs. peak value of magnetic polarization $\hat{J}$ .....	29
Table 1 – Network design .....	24
Table 2 – Error of the specific total loss recalled from the trained neural network compared with the measured values at 1,6 T (point not used during the training).....	25
Table 3 – Error of the specific total loss recalled from the trained neural network compared with the measured values at 1,5 T (point used during the training).....	25

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**DETERMINATION OF MAGNETIC LOSS  
UNDER MAGNETIC POLARIZATION WAVEFORMS  
INCLUDING HIGHER HARMONIC COMPONENTS –  
MEASUREMENT, MODELLING AND CALCULATION METHODS**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC/TR 62383, which is a technical report, has been prepared by IEC technical committee 68: Magnetic alloys and steels.

The text of this technical report is based on the following documents:

Enquiry draft	Report on voting
68/309/DTR	68/315/RVC

Full information on the voting for the approval of this technical report can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

## INTRODUCTION

The specific total loss has to be measured for the design of electrical machines and classification of electrical steel sheets. During the last 20 years, electrical engineers have determined the magnetic induction waveforms of electrical machines [1] to [4]<sup>1)</sup>, and calculated the magnetic power loss under non-sinusoidal waveform of magnetic polarization [5] to [13]. They designed electrical machines using numeric calculation (FEM, BEM) and high speed computers, including non-linear and hysteresis properties of magnetic materials.

Under standard measurement conditions, the specific total loss of electrical steel is to be measured only under the condition of sinusoidal waveform of the magnetic polarization. However, the actual magnetic polarization waveforms of the electric machine are almost always not sinusoidal because of the material behaviour (anisotropy, non-linear B-H performance in high polarization regions such as the stator tooth of electrical machines), because of PWM modulated voltage for variable speed motors and because of the layout of the magnetic circuit and the winding scheme (tooth harmonics).

Specific total loss values obtained by the standard method are not really applicable to an actual electrical machine design because the specific total loss of ferromagnetic material cannot be predicted easily due to non-linear and hysteresis effects, but these higher harmonic polarizations bring about a large increase in magnetic loss.

---

<sup>1)</sup> The figures in square brackets refer to the Bibliography.

# DETERMINATION OF MAGNETIC LOSS UNDER MAGNETIC POLARIZATION WAVEFORMS INCLUDING HIGHER HARMONIC COMPONENTS – MEASUREMENT, MODELLING AND CALCULATION METHODS

## 1 Scope

Nowadays, by computer aided testing (CAT), a.c. magnetic properties of electrical steel sheets can be measured under various measuring conditions automatically. For example, the magnetic loss in the presence of higher harmonic frequency components of magnetic polarization can be measured using the arbitrary waveform synthesizer, digitiser and computer.

The present standard methods (IEC 60404-2, IEC 60404-3 and IEC 60404-10) for the determination of specific total loss are restricted to the sinusoidal waveform of magnetic polarization, and these standards are still important for the characterization of core materials. However, actual waveforms of magnetic polarization in the electrical machines and transformers always include higher harmonic polarizations, and nowadays electrical machines can be designed using numerical methods including higher harmonics. But for these conditions, there is still no standard testing method.

This technical report reviews methods for measurement of the magnetic loss of soft magnetic materials under the condition of magnetic polarization which includes higher harmonic components.

## 2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60404-2, *Magnetic materials – Part 2: Methods of measurement of the magnetic properties of electrical steel sheet and strip by means of an Epstein frame*

IEC 60404-3:1992, *Magnetic materials – Part 3: Methods of measurement of the magnetic properties of magnetic sheet and strip by means of a single sheet tester*

IEC 60404-6, *Magnetic materials – Part 6: Methods of measurement of the magnetic properties of magnetically soft metallic and powder materials at frequencies in the range 20 Hz to 200 kHz by the use of ring specimens*

IEC 60404-10, *Magnetic materials – Part 8: Specifications for individual materials – Section 10: Specification for magnetic materials (iron and steel) for use in relays*