

INTERNATIONAL STANDARD

REDLINE VERSION

**Ferrite cores - Guidelines on dimensions and the limits of surface irregularities -
Part 2: Pot-cores for use in telecommunications, power supply, and filter
applications**

CONTENTS

FOREWORD.....	3
1 Scope.....	5
2 Normative references	5
3 Terms and definitions	5
4 Primary dimensions	5
4.1 Dimensions of pot-cores.....	5
4.1.1 General	5
4.1.2 Principal dimensions	6
4.1.3 Wire-ways.....	8
4.1.4 Effective parameter values	8
4.2 Main dimensions for coil formers	9
5 Limits of surface irregularities	10
5.1 General.....	10
5.2 Examples of surface irregularities.....	10
5.3 Chips and ragged edges.....	11
5.3.1 General	11
5.3.2 Chips and ragged edges on the mating surfaces.....	11
5.3.3 Chips and ragged edges on the other surfaces	11
5.4 Cracks	13
5.5 Pull-out, crystallite and pore locations	14
5.6 Flash	15
Annex A (informative) Pot-core design	16
Annex B (informative) Example of gauges to check the dimensions of pot-cores.....	17
B.1 General.....	17
B.2 Procedure and requirements	18
Bibliography	
Figure 1 – Principal dimensions of pot-cores without back wall slots	6
Figure 2 – Principal dimensions of pot-cores with back wall slots	7
Figure 3 – Main dimensions of coil formers for pot-cores	9
Figure 4 – Examples of surface irregularities	10
Figure 5 – Chips and ragged edge location for pot-cores	11
Figure 6 – Cracks location – Top view	13
Figure 7 – Cracks location – Bottom view	13
Figure 8 – Pull-out, crystallite and pore locations.....	14
Figure 9 – Flash location.....	15
Figure B.1 – Dimensions of gauge A	17
Figure B.2 – Dimensions of gauges B and C.....	18
Table 1 – Principal dimensions of pot-cores	6
Table 2 – Limits for dimensions <i>C</i> and <i>G</i>	7
Table 3 – Minimum wire-way depth	8
Table 4 – Effective parameter values for pot-cores with a centre hole	8
Table 5 – Effective parameter values for pot-cores without a centre hole.....	9

Table 6 – Main dimensions of coil formers for pot-cores.....	10
Table 7 – Area and length references of irregularities for visual inspection.....	12
Table 8 – Limits for cracks	14
Table A.1 – Ratio of diameter to height	16
Table B.1 – Dimensions of gauge A.....	17
Table B.2 – Dimensions of gauges B and C.....	18

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**Ferrite cores - Guidelines on dimensions
and the limits of surface irregularities -
Part 2: Pot-cores for use in telecommunications,
power supply, and filter applications**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 63093-2:2020. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC 63093-2 has been prepared by IEC technical committee 51: Magnetic components, ferrite and magnetic powder materials. It is an International Standard.

This second edition cancels and replaces the first edition published in 2020. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

a) revision of Table 4 and Table 5 according to IEC 60205:2016.

The text of this International Standard is based on the following documents:

Draft	Report on voting
51/1581/FDIS	51/1588/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts in the IEC 63093 series, published under the general title *Ferrite cores - Guidelines on dimensions and the limits of surface irregularities*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

1 Scope

This part of IEC 63093 specifies the dimensions that are of importance for mechanical interchangeability for a preferred range of pot-cores made of ferrite, and the dimensional limits for coil formers to be used with them, as well as the effective parameter values to be used in calculations involving them. It also gives guidelines on the allowable limits of surface irregularities applicable to pot-cores in accordance with the relevant generic specification.

The selection of core sizes and shapes for this document is based on the philosophy of including those sizes which are industrial standards, either by inclusion in a national standard, or by broad-based use in industry. ~~See IEC 62317-1 for more detail concerning the philosophy of selecting core sizes to be included.~~

The general considerations upon which the design of this range of cores is based are given in Annex A.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60205, *Calculation of the effective parameters of magnetic piece parts*

IEC 60401-1, *Terms and nomenclature for cores made of magnetically soft ferrites - Part 1: Terms used for physical irregularities and reference of dimensions*

~~IEC 60424-1, Ferrite cores — Guidelines on the limits of surface irregularities — Part 1: General specification~~

IEC 63093-1, *Ferrite cores - Guidelines on dimensions and the limits of surface irregularities - Part 1: General specification*