



IEC TR 63079

Edition 1.2 2020-04
CONSOLIDATED VERSION

TECHNICAL REPORT



Code of practice for hearing-loop systems (HLS)

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 17.140.50

ISBN 978-2-8322-8141-3

Warning! Make sure that you obtained this publication from an authorized distributor.

REDLINE VERSION



Code of practice for hearing-loop systems (HLS)

CONTENTS

FOREWORD	7
INTRODUCTION	9
1 Scope	10
2 Normative references	10
3 Terms, definitions, signs and symbols	10
3.1 Terms and definitions	10
3.2 Signs and symbols	12
3.2.1 Symbol for an induction-loop	12
3.2.2 Symbol for multiple loops	13
3.2.3 Sign for display in premises where an HLS is installed and for HLS equipment identification	13
3.2.4 Identification of areas where reception of the HLS is not satisfactory	14
4 General	14
4.1 How to use this document	14
4.1.1 Persons addressed	14
4.1.2 Objectives	14
4.2 Specialist advice	15
4.3 Safety aspects	15
4.4 Conforming to existing performance documents	15
5 Technical advice	15
5.1 Complying with this document	15
5.2 Seeking technical advice	16
5.3 The nature of the advice	16
5.4 Professional (consultancy) advice	16
6 Purpose of the system	16
7 Choosing the system supplier	17
7.1 General	17
7.2 Approaching a contractor	17
7.3 Approaching a manufacturer of HLS equipment	17
7.4 Approaching a specialist consultant	17
8 Contractual provisions	18
8.1 Performance specification	18
8.2 Verifying that the completed system delivers its intended performance	18
8.3 Arbitration	18
9 Classification of systems	19
10 Design	20
10.1 General	20
10.2 Symbols	21
10.3 Basic theory	21
10.3.1 Production of a magnetic field	21
10.3.2 Directional pattern of the magnetic field	23
10.3.3 Uniformity of the magnetic field strength	27
10.3.4 Reference points for magnetic field strength	27
10.3.5 Relationship between the requirements of IEC 60118-4 and the characteristics of hearing aids and speech signals	28

10.3.6	Impedance of the loop	29
10.3.7	Selection of the method of driving the loop	30
10.3.8	Current-driven loop	30
10.3.9	Voltage-driven loop	31
10.3.10	Voltage-driven loop with high-level equalization	32
10.3.11	Voltage-driven loop with low-level equalization	34
10.3.12	Use of transformers	34
10.3.13	Effects of building construction	35
10.3.14	Electromagnetic compatibility (EMC)	36
10.3.15	Tone signals	38
10.3.16	Equalization, other than for compensating loop impedance characteristics	38
10.3.17	Multiple loops	38
10.3.18	Protection of loop conductors	41
10.3.19	Automatic gain control (AGC), compression, limiting, noise gating and voice control	42
10.3.20	Signal-to-noise ratio	42
10.3.21	HLS for purposes other than assisted hearing	43
10.3.22	Time-differences between related information streams	44
10.4	System components	44
10.4.1	Final amplifiers	44
10.4.2	Preamplifiers and mixers	44
10.4.3	Signal sources	45
10.5	Objective measurement of intelligibility	52
10.6	Safety and reliability considerations	53
10.7	Designing for monitoring and maintenance	53
10.8	External factors	53
10.8.1	Magnetic noise interference	53
10.8.2	Effect of metal in the building	54
10.9	Magnetic field overspill	54
10.10	The role of the system designer in commissioning	54
11	Responsibility of the installer	54
12	Installation practices and workmanship	56
13	Inspection and testing of wiring	57
14	Commissioning	58
15	Documentation	60
16	Certification	60
17	Acceptance	61
18	Verification	62
19	Owner responsibilities	63
19.1	Signage	63
19.2	User feedback	63
19.3	Staff training	63
20	Operation and maintenance	63
20.1	General	63
20.2	Routine testing	63
20.3	Inspection and servicing	64
20.4	Non-routine attention	65

20.5	Special inspection on appointment of a new maintenance organization	65
20.6	Arrangements for repair of faults or damage	65
20.7	Modifications to the system	66
21	User responsibilities	66
21.1	Responsible person	66
21.2	Logbook	67
Annex A	(informative) HLS monitoring receivers	68
A.1	General	68
A.2	Recommendations for fixed receivers	68
A.3	Recommendations for portable receivers	69
Annex B	(informative) What is a hearing-loop system (HLS) and how does it work?	70
B.1	General	70
B.2	Benefits of HLS (for hearing enhancement)	70
B.3	Limitations of HLS	71
Annex C	(informative) Explanations of the basis of the design formulas	72
C.1	Magnetic field strength	72
C.1.1	Magnetic field strength produced by an element of conductor	72
C.1.2	Field strength produced by a circular loop at a point on its axis	73
C.2	Magnetic field strength at the centre of a rectangular loop	74
C.3	Magnetic field strength at an arbitrary point	76
C.4	Loop conductor sizes and resistances	80
C.4.1	General	80
C.4.2	Resistance of the loop conductor and relation between conductor size and cut-off frequency for a voltage-driven loop	80
C.4.3	Quick reference tables (derived from IEC 60228)	82
C.4.4	Inductance of two parallel wires, leading to the inductance of a rectangular loop	82
C.4.5	Variation of the impedance of a loop of fixed dimensions with conductor resistance	84
C.4.6	High-level equalizer	85
Annex D	(informative) Explanation of the specification and measurement of magnetic field strength of induction-loop systems	88
Annex E	(normative) Specification of the PPM-based field strength meter	90
E.1	General	90
E.2	Checking magnetic field strength meters	91
Annex F	(informative) Magnetic field direction near the loop conductor	92
Annex G	(informative) Direct-to-reverberant sound pressure ratio	95
Annex H	(informative) Model certificates	96
H.1	Design certificate	96
H.2	Installation certificate	97
H.3	Commissioning certificate	98
H.4	Acceptance certificate	100
H.5	Verification certificate (optional)	101
H.6	Inspection and servicing certificate	102
H.7	Modification certificate	104
Annex I	(informative) Measuring STI with hearing loop systems (HLS)	106
I.1	Causes of loss of intelligibility	106
I.2	Measurement method	106

1.2.1	General	106
1.2.2	Limitations of the method.....	106
1.2.3	Measurement equipment	106
1.2.4	Procedure.....	107
Annex J (informative) Example of an architect's specification for an HLS		108
Annex K (informative) Control of time-differences between information presented to a recipient via two transmission channels or media.....		109
K.1	General.....	109
K.2	Audible speech signals	109
K.3	Audible speech signal and video display of the talker.....	109
K.4	Priority.....	109
Bibliography.....		110
Figure 1 – Symbol for use on diagrams		13
Figure 2 – Symbol for multiple loops for use on diagrams		13
Figure 3 – Sign for display in premises to indicate that an HLS is installed and for HLS equipment identification		14
Figure 4 – Sign to show seating areas where HLS reception is not satisfactory.....		14
Figure 5 – Pictorial view of the magnetic field (lines of force) of a rectangular loop.....		22
Figure 6 – Directional response of a hearing aid telecoil		24
Figure 7 – Variation of the strength of the perpendicular component of the magnetic field across an axis of a rectangular loop, with listening height as parameter.....		25
Figure 8 – Variation across the median of a square loop of the perpendicular and coplanar components of the magnetic field at a height ratio $h_n = 1$		26
Figure 9 – Variation across the diagonal of a square loop of the perpendicular and coplanar components of the magnetic field at a height ratio $h_n = 1$		26
Figure 10 – Variation with frequency of the logarithm of the impedance of loops of constant inductance L , with the loop resistance R as parameter		30
Figure 11 – Circuit diagram of a "high-level" equalizer (for insertion between the amplifier and the loop)		34
Figure 12 – Preferred loop layout in a steel-framed building.....		35
Figure 13 – Methods of breaking eddy current paths in metal structures		36
Figure 14 – Filter for attenuating VHF signals picked up by the loop		36
Figure 15 – Methods of "breaking" loops into which interference voltages could be induced by an HLS.....		37
Figure 16 – Multiple loop layouts		39
Figure 17 – Variation across an axis of the system, at a height ratio of 0,32, of the component of the field strength, for a loop system similar to that shown in Figure 16 c), compared with the corresponding variations for a conventional single loop		41
Figure 18 – Horizontal directional response of an omni-directional microphone with its axis vertical: decibel scale		48
Figure 19 – Directional response of a cardioid microphone: decibel scale		48
Figure 20 – Directional response of a supercardioid microphone: decibel scale		49
Figure 21 – Directional response of a hypercardioid microphone: decibel scale		49
Figure 22 – Directional response of a highly directional shotgun (rifle) microphone where $f = 250$ Hz and barrel length is 275 mm.....		49
Figure 23 – Directional response of the same microphone where $f = 2,5$ kHz		49
Figure 24 – Directional response of the same microphone where $f = 10$ kHz		49

Figure 25 – Relative operating distances of directional microphones for equal direct-to-reverberant signal ratios	50
Figure 26 – Two methods of positioning microphones on a conference table	51
Figure 27 – The 3-to-1 ratio for microphone positioning (normal)	51
Figure 28 – A reduced 3-to-1 ratio using angled microphones	51
Figure 29 – Illustrations of good and bad microphone placements	52
Figure 30 – Optimization of the height of the microphone above the table	52
Figure 31 – Measuring field strength of type 2 HLS – Plan views	59
Figure C.1 – Generation of magnetic fields	73
Figure C.2 – Diagram for calculating magnetic field strength at the centre of a rectangular loop	76
Figure C.3 – Diagram for calculating magnetic field strength at an arbitrary point	77
Figure C.4 – Diagram for calculating $\cos\Phi$ and $\sin\Phi$	78
Figure C.5 – Diagram for calculating magnetic field strength at point (x, y, z)	80
Figure C.6 – Circuit diagram of a “high-level” or Poperwell equalizer (for insertion between the amplifier and the loop)	86
Figure C.7 – Frequency response obtained with a high-level equalizer	87
Figure E.1 – "EQ" or "wideband" frequency response: target curve and tolerances on response	90
Figure F.1 – Magnetic field patterns	92
Figure F.2 – Magnetic field directions for a floor-level loop	93
Figure F.3 – Magnetic field directions for a ceiling-level loop	94
Table 1 – Classes of loop system	20
Table 2 – Relative operating distances of directional microphones for equal direct-to-reverberant signal ratios	50
Table C.1 – Factor by which the loop current has to be increased, compared with that required for a given magnetic field strength at the centre of a square loop, to obtain the same field strength for a rectangular loop at a point at height ratio of h_n above or below the centre of the loop	74
Table C.2 – Class 5 flexible annealed copper conductors for standard single-core and multi-core cables	81
Table C.3 – Class 1 solid annealed copper conductors for single-core and multi-core cables	82
Table C.4 – Ratio of approximate to exact inductance	84
Table C.5 – Values of $L_{ z }$	85

INTERNATIONAL ELECTROTECHNICAL COMMISSION

CODE OF PRACTICE FOR HEARING-LOOP SYSTEMS (HLS)

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendments has been prepared for user convenience.

IEC TR 63079 edition 1.1 contains the first edition (2017-04) [documents 29/917/DTR and 29/923/RVC], its amendment 1 (2018-09) [documents 29/983/DTR and 29/992/RVDTR] and its amendment 2 (2020-04) [documents 29/1037/DTR and 29/1046/RVDTR].

In this Redline version, a vertical line in the margin shows where the technical content is modified by amendments 1 and 2. Additions are in green text, deletions are in strikethrough red text. A separate Final version with all changes accepted is available in this publication.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a Technical Report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC TR 63079, which is a Technical Report, has been prepared by IEC technical committee 29: Electroacoustics.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of the base publication and its amendments will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The performance of induction-loop systems is specified in IEC 60118-4, whereas IEC TR 63079 gives recommendations and guidance for their design, planning, installation, testing, operation and maintenance. Provisions for components of a system are given in IEC 62489-1. Methods of calculation and measurement of the magnetic field, in the context of human exposure, are given in IEC 62489-2.

This document takes the form of guidance and recommendations. It should not be quoted as if it were a specification and particular care should be taken to ensure that claims of compliance are not misleading.

Any user claiming compliance with this document is expected to be able to justify any course of action that deviates from its recommendations.

CODE OF PRACTICE FOR HEARING-LOOP SYSTEMS (HLS)

1 Scope

This document, which is a Technical Report, gives recommendations for and guidance on the design, planning, installation, testing, operation and maintenance of a hearing-loop system (HLS) intended for communicating speech, music and/or other signals. It is mainly concerned with HLS for hearing enhancement, in which the signals are communicated to users of hearing aids equipped with magnetic pick-up coils.

This document does not apply to induction-loop systems which use a carrier frequency, nor to other systems for hearing enhancement purposes which do not use magnetic induction.

2 Normative references

~~There are no normative references in this document.~~

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60118-4:2014, *Electroacoustics – Hearing aids – Part 4: Induction-loop systems for hearing aid purposes – System performance requirements*

IEC 60268-16, *Sound system equipment – Part 16: Objective rating of speech intelligibility by speech transmission index*

FINAL VERSION



Code of practice for hearing-loop systems (HLS)



CONTENTS

FOREWORD	7
INTRODUCTION	9
1 Scope	10
2 Normative references	10
3 Terms, definitions, signs and symbols	10
3.1 Terms and definitions	10
3.2 Signs and symbols	12
3.2.1 Symbol for an induction-loop	12
3.2.2 Symbol for multiple loops	13
3.2.3 Sign for display in premises where an HLS is installed and for HLS equipment identification	13
3.2.4 Identification of areas where reception of the HLS is not satisfactory	14
4 General	14
4.1 How to use this document	14
4.1.1 Persons addressed	14
4.1.2 Objectives	14
4.2 Specialist advice	15
4.3 Safety aspects	15
4.4 Conforming to existing performance documents	15
5 Technical advice	15
5.1 Complying with this document	15
5.2 Seeking technical advice	16
5.3 The nature of the advice	16
5.4 Professional (consultancy) advice	16
6 Purpose of the system	16
7 Choosing the system supplier	17
7.1 General	17
7.2 Approaching a contractor	17
7.3 Approaching a manufacturer of HLS equipment	17
7.4 Approaching a specialist consultant	17
8 Contractual provisions	18
8.1 Performance specification	18
8.2 Verifying that the completed system delivers its intended performance	18
8.3 Arbitration	18
9 Classification of systems	19
10 Design	20
10.1 General	20
10.2 Symbols	21
10.3 Basic theory	21
10.3.1 Production of a magnetic field	21
10.3.2 Directional pattern of the magnetic field	23
10.3.3 Uniformity of the magnetic field strength	27
10.3.4 Reference points for magnetic field strength	27
10.3.5 Relationship between the requirements of IEC 60118-4 and the characteristics of hearing aids and speech signals	28

10.3.6	Impedance of the loop	29
10.3.7	Selection of the method of driving the loop	30
10.3.8	Current-driven loop	30
10.3.9	Voltage-driven loop	31
10.3.10	Voltage-driven loop with high-level equalization	32
10.3.11	Voltage-driven loop with low-level equalization	34
10.3.12	Use of transformers	34
10.3.13	Effects of building construction	35
10.3.14	Electromagnetic compatibility (EMC)	36
10.3.15	Tone signals	38
10.3.16	Equalization, other than for compensating loop impedance characteristics	38
10.3.17	Multiple loops	38
10.3.18	Protection of loop conductors	41
10.3.19	Automatic gain control (AGC), compression, limiting, noise gating and voice control	42
10.3.20	Signal-to-noise ratio	42
10.3.21	HLS for purposes other than assisted hearing	43
10.3.22	Time-differences between related information streams	44
10.4	System components	44
10.4.1	Final amplifiers	44
10.4.2	Preamplifiers and mixers	44
10.4.3	Signal sources	45
10.5	Objective measurement of intelligibility	52
10.6	Safety and reliability considerations	53
10.7	Designing for monitoring and maintenance	53
10.8	External factors	53
10.8.1	Magnetic noise interference	53
10.8.2	Effect of metal in the building	54
10.9	Magnetic field overspill	54
10.10	The role of the system designer in commissioning	54
11	Responsibility of the installer	54
12	Installation practices and workmanship	56
13	Inspection and testing of wiring	57
14	Commissioning	58
15	Documentation	60
16	Certification	60
17	Acceptance	61
18	Verification	62
19	Owner responsibilities	63
19.1	Signage	63
19.2	User feedback	63
19.3	Staff training	63
20	Operation and maintenance	63
20.1	General	63
20.2	Routine testing	63
20.3	Inspection and servicing	64
20.4	Non-routine attention	65

20.5	Special inspection on appointment of a new maintenance organization	65
20.6	Arrangements for repair of faults or damage	65
20.7	Modifications to the system	66
21	User responsibilities	66
21.1	Responsible person	66
21.2	Logbook	67
Annex A	(informative) HLS monitoring receivers	68
A.1	General	68
A.2	Recommendations for fixed receivers	68
A.3	Recommendations for portable receivers	69
Annex B	(informative) What is a hearing-loop system (HLS) and how does it work?	70
B.1	General	70
B.2	Benefits of HLS (for hearing enhancement)	70
B.3	Limitations of HLS	71
Annex C	(informative) Explanations of the basis of the design formulas	72
C.1	Magnetic field strength	72
C.1.1	Magnetic field strength produced by an element of conductor	72
C.1.2	Field strength produced by a circular loop at a point on its axis	72
C.2	Magnetic field strength at the centre of a rectangular loop	74
C.3	Magnetic field strength at an arbitrary point	75
C.4	Loop conductor sizes and resistances	80
C.4.1	General	80
C.4.2	Resistance of the loop conductor and relation between conductor size and cut-off frequency for a voltage-driven loop	80
C.4.3	Quick reference tables (derived from IEC 60228)	81
C.4.4	Inductance of two parallel wires, leading to the inductance of a rectangular loop	81
C.4.5	Variation of the impedance of a loop of fixed dimensions with conductor resistance	84
C.4.6	High-level equalizer	84
Annex D	(informative) Explanation of the specification and measurement of magnetic field strength of induction-loop systems	87
Annex E	(normative) Specification of the PPM-based field strength meter	89
E.1	General	89
E.2	Checking magnetic field strength meters	90
Annex F	(informative) Magnetic field direction near the loop conductor	91
Annex G	(informative) Direct-to-reverberant sound pressure ratio	94
Annex H	(informative) Model certificates	95
H.1	Design certificate	95
H.2	Installation certificate	96
H.3	Commissioning certificate	97
H.4	Acceptance certificate	99
H.5	Verification certificate (optional)	100
H.6	Inspection and servicing certificate	101
H.7	Modification certificate	103
Annex I	(informative) Measuring STI with hearing loop systems (HLS)	105
I.1	Causes of loss of intelligibility	105
I.2	Measurement method	105

1.2.1	General	105
1.2.2	Limitations of the method.....	105
1.2.3	Measurement equipment	105
1.2.4	Procedure.....	106
Annex J (informative) Example of an architect's specification for an HLS		107
Annex K (informative) Control of time-differences between information presented to a recipient via two transmission channels or media.....		108
K.1	General.....	108
K.2	Audible speech signals	108
K.3	Audible speech signal and video display of the talker.....	108
K.4	Priority.....	108
Bibliography.....		109
Figure 1 – Symbol for use on diagrams		13
Figure 2 – Symbol for multiple loops for use on diagrams		13
Figure 3 – Sign for display in premises to indicate that an HLS is installed and for HLS equipment identification		14
Figure 4 – Sign to show seating areas where HLS reception is not satisfactory.....		14
Figure 5 – Pictorial view of the magnetic field (lines of force) of a rectangular loop.....		22
Figure 6 – Directional response of a hearing aid telecoil		24
Figure 7 – Variation of the strength of the perpendicular component of the magnetic field across an axis of a rectangular loop, with listening height as parameter		25
Figure 8 – Variation across the median of a square loop of the perpendicular and coplanar components of the magnetic field at a height ratio $h_n = 1$		26
Figure 9 – Variation across the diagonal of a square loop of the perpendicular and coplanar components of the magnetic field at a height ratio $h_n = 1$		26
Figure 10 – Variation with frequency of the logarithm of the impedance of loops of constant inductance L , with the loop resistance R as parameter		30
Figure 11 – Circuit diagram of a "high-level" equalizer (for insertion between the amplifier and the loop)		34
Figure 12 – Preferred loop layout in a steel-framed building.....		35
Figure 13 – Methods of breaking eddy current paths in metal structures		36
Figure 14 – Filter for attenuating VHF signals picked up by the loop		36
Figure 15 – Methods of "breaking" loops into which interference voltages could be induced by an HLS.....		37
Figure 16 – Multiple loop layouts		39
Figure 17 – Variation across an axis of the system, at a height ratio of 0,32, of the component of the field strength, for a loop system similar to that shown in Figure 16 c), compared with the corresponding variations for a conventional single loop		41
Figure 18 – Horizontal directional response of an omni-directional microphone with its axis vertical: decibel scale		48
Figure 19 – Directional response of a cardioid microphone: decibel scale		48
Figure 20 – Directional response of a supercardioid microphone: decibel scale		49
Figure 21 – Directional response of a hypercardioid microphone: decibel scale		49
Figure 22 – Directional response of a highly directional shotgun (rifle) microphone where $f = 250$ Hz and barrel length is 275 mm.....		49
Figure 23 – Directional response of the same microphone where $f = 2,5$ kHz		49
Figure 24 – Directional response of the same microphone where $f = 10$ kHz		49

Figure 25 – Relative operating distances of directional microphones for equal direct-to-reverberant signal ratios	50
Figure 26 – Two methods of positioning microphones on a conference table	51
Figure 27 – The 3-to-1 ratio for microphone positioning (normal)	51
Figure 28 – A reduced 3-to-1 ratio using angled microphones	51
Figure 29 – Illustrations of good and bad microphone placements	52
Figure 30 – Optimization of the height of the microphone above the table	52
Figure 31 – Measuring field strength of type 2 HLS – Plan views	59
Figure C.1 – Generation of magnetic fields	73
Figure C.2 – Diagram for calculating magnetic field strength at the centre of a rectangular loop	75
Figure C.3 – Diagram for calculating magnetic field strength at an arbitrary point	77
Figure C.4 – Diagram for calculating $\cos\Phi$ and $\sin\Phi$	77
Figure C.5 – Diagram for calculating magnetic field strength at point (x, y, z)	79
Figure C.6 – Circuit diagram of a “high-level” or Poperwell equalizer (for insertion between the amplifier and the loop)	86
Figure C.7 – Frequency response obtained with a high-level equalizer	86
Figure E.1 – "EQ" or "wideband" frequency response: target curve and tolerances on response	89
Figure F.1 – Magnetic field patterns	91
Figure F.2 – Magnetic field directions for a floor-level loop	92
Figure F.3 – Magnetic field directions for a ceiling-level loop	93
Table 1 – Classes of loop system	20
Table 2 – Relative operating distances of directional microphones for equal direct-to-reverberant signal ratios	50
Table C.1 – Factor by which the loop current has to be increased, compared with that required for a given magnetic field strength at the centre of a square loop, to obtain the same field strength for a rectangular loop at a point at height ratio of h_n above or below the centre of the loop	73
Table C.2 – Class 5 flexible annealed copper conductors for standard single-core and multi-core cables	81
Table C.3 – Class 1 solid annealed copper conductors for single-core and multi-core cables	81
Table C.4 – Ratio of approximate to exact inductance	84
Table C.5 – Values of $L_{ z }$	84

INTERNATIONAL ELECTROTECHNICAL COMMISSION

CODE OF PRACTICE FOR HEARING-LOOP SYSTEMS (HLS)

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This consolidated version of the official IEC Standard and its amendments has been prepared for user convenience.

IEC TR 63079 edition 1.1 contains the first edition (2017-04) [documents 29/917/DTR and 29/923/RVC], its amendment 1 (2018-09) [documents 29/983/DTR and 29/992/RVDTR] and its amendment 2 (2020-04) [documents 29/1037/DTR and 29/1046/RVDTR].

This Final version does not show where the technical content is modified by amendments 1 and 2. A separate Redline version with all changes highlighted is available in this publication.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a Technical Report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC TR 63079, which is a Technical Report, has been prepared by IEC technical committee 29: Electroacoustics.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of the base publication and its amendments will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The performance of induction-loop systems is specified in IEC 60118-4, whereas IEC TR 63079 gives recommendations and guidance for their design, planning, installation, testing, operation and maintenance. Provisions for components of a system are given in IEC 62489-1. Methods of calculation and measurement of the magnetic field, in the context of human exposure, are given in IEC 62489-2.

This document takes the form of guidance and recommendations. It should not be quoted as if it were a specification and particular care should be taken to ensure that claims of compliance are not misleading.

Any user claiming compliance with this document is expected to be able to justify any course of action that deviates from its recommendations.

CODE OF PRACTICE FOR HEARING-LOOP SYSTEMS (HLS)

1 Scope

This document, which is a Technical Report, gives recommendations for and guidance on the design, planning, installation, testing, operation and maintenance of a hearing-loop system (HLS) intended for communicating speech, music and/or other signals. It is mainly concerned with HLS for hearing enhancement, in which the signals are communicated to users of hearing aids equipped with magnetic pick-up coils.

This document does not apply to induction-loop systems which use a carrier frequency, nor to other systems for hearing enhancement purposes which do not use magnetic induction.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60118-4:2014, *Electroacoustics – Hearing aids – Part 4: Induction-loop systems for hearing aid purposes – System performance requirements*

IEC 60268-16, *Sound system equipment – Part 16: Objective rating of speech intelligibility by speech transmission index*